

MAT1 Microphone Adapter

The MAT1 is intended to interface an unbalanced electret microphone to a balanced microphone input with phantom power such as those found on professional audio equipment. The unit has unity gain and provides 6.8V bias voltage to the electret microphone.

Always use good quality cables of the type described in these instructions and only connect the unit as described below. Always install the unit in a dry location away from extremes of temperature and humidity.

The MAT1 should not be used for any other purpose than those described in this leaflet unless written permission has been obtained from Ampetronic Ltd.

1. Input connection.

The input should be connected to an unbalanced electret microphone such as those supplied by Ampetronic Ltd using a single core screened cable terminated in 3.5mm mono jack plug. This cable *must not* exceed 3m otherwise interference may be introduced into the system.

A 6.8V low current bias voltage is supplied to the microphone. To avoid damage, any batteries fitted in the microphone should be removed before use with the MAT1, and the microphone manufacturer's advice should be followed if necessary to configure the microphone for bias supply.

2. Output connection.

The MAT1 output should be connected to a balanced microphone input which provides minimum 12V phantom power, using screened balanced cabling and terminated in a female XLR socket.

The microphone input must supply 12-48V balanced phantom power for the MAT1 to function correctly. All balanced microphone inputs on Ampetronic equipment are suitable for connection to the MAT1 when set to supply phantom power.

The logo for Ampetronic, featuring the word "AMPETRONIC" in a bold, blue, sans-serif font, enclosed within a blue rectangular border with a slight 3D effect.

Listen to the difference

Warranty Information

This product carries a five year parts and labour warranty from date of shipment from Ampetronic. To qualify for the five year warranty, the product must be registered at www.ampetronic.com (products/warranty), without which the warranty will be valid for two years only.

The warranty could be invalidated if the instructions in this handbook are not followed correctly, or if the unit is misused in any way.

The MAT1 is designed and manufactured in England by Ampetronic Ltd.

DECLARATION OF CONFORMITY

Manufacturer: Ampetronic Ltd.
Address: Northern Road, Newark,
Nottinghamshire, NG24 2ET,
United Kingdom.

Declares that the product:

Description: Microphone Adapter
Type Name: MAT 1

Conforms to the following Directive(s) and Norm(s):

Directive 2004/108/EC
EMC: EN55103-1 : 2009 Emission
EN55103-2 : 2009 Immunity

Directive 2006/95/EC
Safety: EN60065 : 2002

Date: January 2011
J.R. Pieters
Managing Director
Ampetronic Ltd.

Ampetronic Ltd,
Northern Road, Newark,
Nottinghamshire, NG24 2ET
United Kingdom

Tel: +44 (0) 1636 610062 Fax: +44 (0) 1636 610063
www.ampetronic.com Email: sales@ampetronic.com

MAT1 Microphone Adapter

The MAT1 is intended to interface an unbalanced electret microphone to a balanced microphone input with phantom power such as those found on professional audio equipment. The unit has unity gain and provides 6.8V bias voltage to the electret microphone.

Always use good quality cables of the type described in these instructions and only connect the unit as described below. Always install the unit in a dry location away from extremes of temperature and humidity.

The MAT1 should not be used for any other purpose than those described in this leaflet unless written permission has been obtained from Ampetronic Ltd.

1. Input connection.

The input should be connected to an unbalanced electret microphone such as those supplied by Ampetronic Ltd using a single core screened cable terminated in 3.5mm mono jack plug. This cable *must not* exceed 3m otherwise interference may be introduced into the system.

A 6.8V low current bias voltage is supplied to the microphone. To avoid damage, any batteries fitted in the microphone should be removed before use with the MAT1, and the microphone manufacturer's advice should be followed if necessary to configure the microphone for bias supply.

2. Output connection.

The MAT1 output should be connected to a balanced microphone input which provides minimum 12V phantom power, using screened balanced cabling and terminated in a female XLR socket.

The microphone input must supply 12-48V balanced phantom power for the MAT1 to function correctly. All balanced microphone inputs on Ampetronic equipment are suitable for connection to the MAT1 when set to supply phantom power.

The logo for Ampetronic, featuring the word "AMPETRONIC" in a bold, blue, sans-serif font, enclosed within a blue rectangular border with a slight 3D effect.

Listen to the difference

Warranty Information

This product carries a five year parts and labour warranty from date of shipment from Ampetronic. To qualify for the five year warranty, the product must be registered at www.ampetronic.com (products/warranty), without which the warranty will be valid for two years only.

The warranty could be invalidated if the instructions in this handbook are not followed correctly, or if the unit is misused in any way.

The MAT1 is designed and manufactured in England by Ampetronic Ltd.

DECLARATION OF CONFORMITY

Manufacturer: Ampetronic Ltd.
Address: Northern Road, Newark,
Nottinghamshire, NG24 2ET.
United Kingdom.

Declares that the product:

Description: Microphone Adapter
Type Name: MAT 1

Conforms to the following Directive(s) and Norm(s):

Directive 2004/108/EC
EMC: EN55103-1 : 2009 Emission
EN55103-2 : 2009 Immunity

Directive 2006/95/EC
Safety: EN60065 : 2002

Date: January 2011
J.R. Pieters
Managing Director
Ampetronic Ltd.

Ampetronic Ltd,
Northern Road, Newark,
Nottinghamshire, NG24 2ET
United Kingdom

Tel: +44 (0) 1636 610062 Fax: +44 (0) 1636 610063
www.ampetronic.com Email: sales@ampetronic.com